

## QCK-J-18

### 7mm Connectors, DC~18GHz

Features:  
\* High Precision

Applications:  
\* Calibration  
\* Laboratory Test



#### Description

With the components in these kits you can make error-corrected measurements of devices supplied with 7mm connectors from DC to 18 GHz.

#### Components

Part Number	Description	Frequency	Impedance	VSWR	Phase Accuracy	Inner Conductor	Outer Conductor	Size
		(GHz)	( $\Omega$ )	(Max.)	( $^{\circ}$ , Max.)			(mm)
QOJC-18	7mm open	DC~18	50	-	$\pm 1$	Gold plated beryllium copper	Gold plated beryllium copper	-
QSJC-18	7mm short			-	$\pm 1$			-
QCT-J-C-18	7mm termination			1.048	-			-
QW-J1-CK	7mm torque wrench			-	-	Nickel plated tool steel (Head)	Aluminium, anodised (Handle)	19.1mm (Opening size)
QANJC-M*	N male to 7mm adapter			1.06	-	Gold plated beryllium copper	Passivated stainless steel	-
QANJC-F*	N female to 7mm adapter							
Storage Box				-	-	-	-	Wood

\* \* Equal phase adapter

#### How To Orders

**QCK-J-18-6** All the 6 components in one box.

To order a single component, specify the part number in the first column.