



# QPD2-40000-67000-12-V

2-Way, 40~67GHz

Features: Applications:

\* Small Size \* Amplifiers

\* Low Insertion Loss \* Mixers

\* Antennas

\* Laboratory Test

## **Electrical**

Frequency: 40~67GHz
Insertion Loss: 2.1dB max.
Input VSWR: 1.8 max.
Output VSWR: 1.8 max.
Isolation: 18dB min.

Amplitude Balance:  $\pm 0.6$ dB max. Phase Balance:  $\pm 8^{\circ}$  max. Impedance:  $50\Omega$ 

Power @SUM Port: 12W max. as divider

1W max. as combiner

### Mechanical

Size\*1: 15.2\*25.4\*10mm

0.598\*1\*0.394in 1.85mm Female

Connectors: 1.85mm Female


Mounting: 2-Φ2.6mm through-hole

[1] Exclude connectors.

#### **Environmental**

Operation Temperature: -55~+85°C Non-operation Temperature: -55~+100°C

# **Outline Drawings**



Unit: mm [in]

Tolerance: ±0.5mm [±0.02in]

# **How To Order**

QPD2-40000-67000-12-V

Customization is available upon request.

www.qualwave.com