

## QCK-2-50

### 2.4mm Connectors, 0.1~50GHz

Features:  
\* High Precision

Applications:  
\* Calibration  
\* Laboratory Test



#### Description

With the components in the kit you can make error-corrected measurements of devices supplied with 2.4mm connectors from 0.1 to 50 GHz.

#### Components

Part Number	Description	Frequency	VSWR	Phase Accuracy	Inner Conductor	Outer Conductor	Size
		(GHz)	(Max.)	( °, Max.)			(mm)
QO2C-M-50	2.4mm male open	0.1-2	-	±0.5	-	-	-
		2-20		±1.25			
QO2C-F-50	2.4mm female open	20-40	-	±1.75	-	-	-
		40-50		±2.25			
QS2C-M-50	2.4mm male short	0.1-2	-	±0.5	-	-	-
		2-20		±1.25			
QS2C-F-50	2.4mm female short	20-40	-	±1.5	-	-	-
		40-50		±2.0			
QCT-2-C-M-50	2.4mm male termination	0.1~4	1.016	-	-	-	-
		4-20	1.04				
QCT-2-C-F-50	2.4mm female termination	20-26.5	1.065	-	-	-	-
		26.5-50	1.106				
QW-21-CK	2.4mm torque wrench	-	-	-	Nickel plated tool steel (Head)	Alumina (Handle)	8.1 (Opening)
QA22C-MM*	2.4mm male to 2.4mm male adapter	0.1-50	1.22	-	-	-	-
QA22C-MF*	2.4mm male to 2.4mm female adapter			-			
QA22C-FF*	2.4mm female to 2.4mm female adapter			-			
Storage Box		-	-	-	Wood		275*200*80/ 145*145*60

“\*” Equal phase adapter

#### How To Order

**QCK-2-50-10** All the 10 components in one box.