

QCK-V-67

1.85mm Connectors, DC~67GHz

Features:
* High Precision

Applications:
* Calibration
* Laboratory Test



Description

With the components in the kit you can make error-corrected measurements of devices supplied with 1.85mm connectors from DC to 67 GHz.

Components

Part Number	Description	Frequency	VSWR	Phase Accuracy	Size
		(GHz)	(Max.)	(°, Max.)	(mm)
QOVC-M-67	1.85mm male open	DC-20 20-67	-	±2.5	-
QOVC-F-67	1.85mm female open			±5.0	-
QSVC-M-67	1.85mm male short	DC-67	-	±2.0	-
QSVC-F-67	1.85mm female short				-
QCT-V-C-M-67	1.85mm male termination	DC-67	1.15	-	-
QCT-V-C-F-67	1.85mm female termination				-
QW-V1-CK	1.85mm torque wrench	-	-	-	8.1 (Opening size)
QAVVC-MM*	1.85mm male to 1.85mm male adapter	DC-26.5 26.5-40 40-67	1.15 1.22 1.33	-	-
QAVVC-MF*	1.85mm male to 1.85mm female adapter				-
QAVVC-FF*	1.85mm female to 1.85mm female adapter				-
Storage Box		-	-	-	-

“*” Equal phase adapter

How To Order

QCK-V-67-10 All the 10 components in one box.